

REMARKS

This Preliminary Amendment cancels original claims 1 to 8 in the underlying PCT Application No. PCT/EP2005/055307 and adds new claims 9 to 17. The new claims conform the claims to the U.S. Patent and Trademark Office rules and do not add new matter to the application.

In accordance with 37 C.F.R. § 1.125, the Substitute Specification (including the Abstract, but without the claims) contains no new matter. The amendments reflected in the Substitute Specification (including the Title and Abstract) are to conform the Specification and Abstract to U.S. Patent and Trademark Office rules or to correct informalities. As required by 37 C.F.R. § 1.121 and § 1.125, a Marked Up Version Of The Substitute Specification comparing the Specification of record and the Substitute Specification also accompanies this Preliminary Amendment. In the Marked Up Version, underlining indicates added text and "strike-throughs" and double-brackets indicate deleted text. Approval and entry of the Substitute Specification (including Abstract) are respectfully requested.

Also enclosed is a translated copy of the International Search Report. The Search Report includes a list of documents that were considered by the Examiner in the underlying PCT application.

The underlying PCT Application No. PCT/EP2005/055307 includes an English translation of the International Preliminary Examination Report.

It is asserted that the subject matter of the present application is new, non-obvious, and useful. Prompt consideration and allowance of the application are respectfully requested.

Respectfully Submitted,
KENYON & KENYON LLP

Dated: 6/9/2006

By: 

Gerard A. Messina
Reg. No. 35,952

One Broadway
New York, New York 10004
Telephone: (212) 425-7200

CUSTOMER NO. 26646

RESISTIVE PARTICLE SENSORS HAVING MEASURING ELECTRODES

~~Background Information~~ FIELD OF THE INVENTION

The present invention relates to a sensor for determining the concentration of particles in gases, in particular of soot particles, ~~as recited in the preamble of Claim 1.~~

5 BACKGROUND INFORMATION

Due to the environment-friendly efforts to reduce soot emissions of diesel engines, the need arises to determine the concentration of soot particles in the exhaust gas in a simple manner. In particular, monitoring the soot level downstream from a diesel
10 particulate filter (DPF) during the operation of the vehicle is useful. In addition, it is necessary to predict the load of a diesel particulate filter for regeneration monitoring to achieve high system reliability.

To determine the soot concentration in the exhaust gas of internal
15 combustion engines, a sensor having a device for detecting soot particles may be installed in the exhaust pipe.

~~DE~~ German Patent documents nos. 101 33 384 A1 and DE-33 04 548 A1
~~described~~ discuss a resistive particle sensor, which has at least one non-conductive substrate element, measuring electrodes being
20 situated on a substrate element. The measuring electrodes ~~are~~
~~usually~~ may be implemented in an interdigital comb structure. In an interdigital comb structure, each measuring electrode is formed by a series of individual finger electrodes, which are electrically connected to one another. The finger electrodes of both measuring
25 electrodes alternately engage with one another, hence the designation "interdigital comb structure." Deposition of particles on the measuring surface between the electrodes, known

E 1321878004

as leakage current surface, results in a change in conductivity or impedance of the measuring surface between the fingers of the electrodes. For example, the resistance, the real part of the impedance, decreases with increasing particle concentration on the measuring surface. Alternatively, an increasing current at constant voltage applied between the measuring electrodes may be measured. The deposition, i.e., the deposition rate of particles, may be derived from the change in the particular measured quantity - the sensor signal.

This measuring method corresponds to an accumulating measuring principle, and the sooted sensor surfaces must therefore be freed of the conductive soot particles from time to time whenever a defined saturation current or another threshold value is attained. A high voltage to burn the soot particles via the current flow may be applied between the electrodes for regenerating the sooted surface. Alternatively, an integrated heater may heat the sensor affected by soot, so that the accumulated soot is fully burned off. After the soot particles have been burned off, the sensor is in its original state again, and a new measuring cycle including re-deposition and measurement of particles is thus made possible. Measuring and regeneration phases thus always alternate over time.

One disadvantage of this procedure is that no new deposition of particles is possible during the burn-off. Even after regeneration, soot cannot accumulate immediately; due to its thermal inertia, the sensor needs a certain time for the exhaust gas to bring the sensor element to its working temperature. Since no soot may accumulate during regeneration and the subsequent cooling phase of the sensor, the sensor is insensitive to any soot concentration present during these phases. Therefore, a measuring phase that is as long as possible is desirable. At the same time, the measured value must be large enough to enable early and meaningful determination of the particle concentration.

~~Advantages of the Invention~~

SUMMARY OF THE INVENTION

The sensor according to the exemplary embodiment and/or exemplary method of the present invention for determining the concentration of particles in gases, in particular of soot particles, has the advantage that the sensitivity of measurement is improved. In particular, the deposition rate of particles at constant particle concentration and thus the measured values also increase.

At the same time, the measuring phase is increased compared to the regeneration phase. Thus, using simple means, the sensor may be kept in the measuring phase for a longer time before the sensor signal shows saturation phenomena.

~~Advantageous refinements of the sensor are specified in the subclaims and described in the description.~~

~~Drawing~~

~~Exemplary embodiments of the present invention are elucidated in greater detail with reference to the drawing and the description that follows.~~

BRIEF DESCRIPTION OF THE DRAWINGS

~~Figures~~Figure 1a and ~~1b each show~~shows an exemplary embodiment of a particle sensor having measuring electrodes situated on a substrate element, in top view, ~~and~~.

~~Figures 2a, 2b~~Figure 1b shows another exemplary embodiment of a particle sensor having measuring electrodes situated on a substrate element, in top view, and

Figure 2a shows another exemplary embodiment of a particle sensor having measuring electrodes situated on a substrate element, in top view.

Figure 2b shows another exemplary embodiment of a particle sensor having measuring electrodes situated on a substrate element, in top view.

- 5 Figure 2c each shows another exemplary embodiment of a particle sensor having measuring electrodes situated on a substrate element, in top view.

~~Detailed Description of the Exemplary Embodiments~~

DETAILED DESCRIPTION

- 10 In a first exemplary embodiment according to Figure 1a, sensor 1 for determining the concentration of particles in gases, in particular of soot particles, has a substrate element 5, on which a first 10 and a second 15 measuring electrode are situated as a measuring device. The space between measuring electrodes 10, 15
15 is used as measuring area 12, on which the particles to be detected are deposited. The two measuring electrodes 10, 15 are connectable to a measuring and control unit (not shown in the figures) via contacts 20, 25 and a voltage may be applied to them. The measured value changes as a function of the state of particle deposition
20 on measuring area 20. The measured value of resistance (impedance) or current intensity value measured via measuring electrodes 10, 15 is a function of the measuring mode.

- As explained previously, the soot concentration in a gas may ultimately be determined from the measured values. The two
25 measuring electrodes 10, 15 are configured according to the exemplary embodiment and/or exemplary method of the present invention in such a way that by applying a voltage between measuring electrodes 10, 15 an asymmetric electric field is formed on measuring area 12. A symmetric electric field is characterized in
30 that the field has a constant direction and intensity all over the field. Such a field is formed, for example, by the interdigital comb electrodes known from the related art. The individual finger electrodes are typically implemented by unstructured, linear track

conductors, which are all parallel to one another. This results in a constant electric field between the finger electrodes.

However, as Figure 1 shows, in sensor 1, sides 30, 35 of first 10 and second 15 measuring electrodes, facing one another, are not parallel to one another. Instead, the distance between first 10 and second 15 measuring electrode decreases or increases continuously along the electrode. This creates an area having sides 30, 35 of measuring electrodes 10, 15, situated closely next to one another, and an area having sides 30, 35 of measuring electrodes 10, 15 situated wide apart. The transition from one area to the other is smooth and continuous. A non-constant field is created by applying a voltage. Particles that deposit on measuring area 12 of sensor 1 cause a reduction in resistance between measuring electrodes 10, 15 by forming conductive paths and thus create a sensor current.

A conductive path is first produced in the area of sides 30, 35 situated close to one another. Since the distance between measuring electrodes 10, 15 is very narrow at this point, a relatively slight particle deposition is sufficient for forming a conductive path and triggering a measuring signal. The sensitivity of sensor 1 is thus increased. As further particles deposit, conductive paths are also formed between sides 30, 35 of measuring electrodes 10, 15, which are farther apart. Due to the percolation characteristics of the deposited soot, whenever an additional conductive path is completed, a stronger increase in conductivity of the entire measuring area 12 takes place, which may be determined via measuring electrodes 10, 15. A stronger signal increase is thus achieved over a longer time period than would be possible in the case of measuring electrodes arranged in parallel. After short-circuiting measuring electrodes 10, 15 along all sides 30, 35, further deposits additionally keep increasing the conductivity continuously, i.e., measurement is also possible during this phase. Since the special configuration and arrangement of measuring electrodes 10, 15 allows a larger measuring area 12 to be formed for particle deposition, higher currents may also be achieved before they reach the saturation range compared to previously known

interdigital measuring electrodes. The sensor signal is thus strengthened.

A varying distance between the finger electrodes may also be achieved in a conventional interdigital comb structure by modifying its shape. As Figure 1b shows, at least one measuring electrode 10, 15 may have finger electrodes 40 having varying widths. While in Figure 1a, first and second measuring electrodes 10, 15 are triangular, in Figure 2b individual finger electrodes 40 of a measuring electrode 10, 15 are triangular. The distance between two adjacent finger electrodes 40 thus changes continuously along the length of finger electrodes 40. This yields the same advantageous effects as described for the first embodiment. The pointed design also produces areas having a controlled direction of preferential growth of the deposited soot particles.

All exemplary embodiments described so far have constantly smooth, unstructured sides of measuring electrodes 10, 15 or of individual finger electrodes 40. Alternatively (Figure 2a) or additionally (Figures 2b, 2c), i.e., combined to form a varying distance between measuring electrodes 10, 15 or finger electrodes 40, it is proposed that at least one measuring electrode 10, 15 has a structure 45 along side 30, 35 facing the other measuring electrode 15, 10 or along finger electrodes 40. Structure 45 is formed by regularly arranged tips, squares, dots, or other geometric shapes. Such structures 45 on the electrode sides result in increased field step-up when a voltage is applied. Structured finger electrodes 40, as in Figure 2a, alone result in a non-constant electric field on measuring area 12. This increase in field step-up causes polarizable or already charged particles to deposit preferentially compared to electrodes without structured sides for the same voltage applied. The particle deposition rate thus increases due to the increased field gradients. Consequently, higher sensor currents are achieved for a given particle concentration. This may make the use of simplified measuring electronics in the control unit for signal analysis possible, since leakage currents or EMC (electromagnetic compatibility) currents have only a slight interfering effect.

Summarizing, measuring electrodes 10, 15 are configured in all
embodiments in such a way that by applying a voltage between
measuring electrodes 10, 15 an asymmetric electric field is formed
on measuring area 12. The asymmetric electric field is an electric
5 field that is non-homogeneous in space. The special design of the
field distribution makes targeted particle deposition control in
space possible. In particular, the formation of conductive paths
in preferred areas may be controlled. Path growth over time may
also be steered in a desired direction. If necessary, more than
10 two measuring electrodes 10, 15 may be provided for this purpose,
for example, at least one central electrode (not shown in the
figures) may be additionally provided between first and second
measuring electrodes 10, 15. The geometric shape of and the
potential applied to all electrodes is to be adapted to the desired
15 field distribution.

~~Abstract~~ ABSTRACT OF THE DISCLOSURE

A sensor ~~(1)~~ for determining the concentration of particles in gases, in particular of soot particles, has at least one substrate element ~~(5)~~, and a measuring area ~~(12)~~ between at least one first ~~(10)~~ and one second ~~(15)~~ measuring electrode, the two measuring electrodes ~~(10, 15)~~ being configured ~~in such a way~~ so that by applying a voltage between the measuring electrodes ~~(10, 15)~~, an asymmetric electric field is formed on the measuring area ~~(12)~~. The sides ~~(30, 35)~~ of the first ~~(10)~~ and second ~~(15)~~ measuring electrodes, facing one another, may not be parallel to one another, for example. Furthermore, at least one measuring electrode ~~(10, 15)~~ may have a structure ~~(45)~~ along the side ~~(30, 35)~~ facing the other measuring electrode ~~(15, 10)~~ or along the finger electrodes ~~(40)~~.

15 ~~(Figure 2b)~~